

# EASO STEREO CO., LTD.

E-mail: audiopro@ms10.hinet.net  
easoco@ms17.hinet.net

4F, No.951, Chung-Cheng Rd., Chung-Ho City.

Taipei. 235 Taiwan. R.O.C.

Tel: 886-2-8228 1100 Fax: 886-2-8228 6101

## ***Mobile Active Hi to Low Converter 6-Channel Active Frequency Converter***



- ***6-Channel Active High to Low Level Converter***
- ***The Functions of the AFC (Active Frequency Converter)***
- ***Ground Isolation Jumper Selector (GND / ISO / 200 ohm)***
- ***Sum Selected Channels Into The Main Channels with AFC***
- ***Gold Plated RCA ( Type ) Connectors & Cover for Selector***

### ***HTOL Technical Data:***

<b>Power Source:</b>	14.4 Volts DC Negative Ground,
<b>Maximum Speaker-level Input:</b>	60Watts at 4 ohm
<b>Maximum Output Level:</b>	9.5V
<b>Output Gain:</b>	+ / - 12dB
<b>Frequency Response:</b>	10 Hz ~ 22 KHz
<b>Total Harmonic Distortion:</b>	<0.01% THD at 1V Output Level
<b>Input Impedance:</b>	180ohm
<b>Power Draw:</b>	200mA
<b>Fuse:</b>	1A
<b>Remote Output Current:</b>	Max. 1A
<b>Dimensions:</b>	162(W)mm x 150(D)mm x 42(H)mm
<b>Weight:</b>	0.75Kgs

***OEM and ODM orders are welcome***

<http://www.easoco.com.tw>