

EASO STEREO CO., LTD.

E-mail: audiopro@ms10.hinet.net
easoco@ms17.hinet.net

4F, No.951, Chung-Cheng Rd., Chung-Ho City.

Taipei. 235 Taiwan. R.O.C.

Tel: 886-2-8228 1100 Fax: 886-2-8228 6101

4 BAND PARAMETRIC EQUALIZER PRE-AMP **High Performance Pre-Amp EMQ-8**



MODEL NO.: EMQ-8

OEM and ODM orders are welcome

- **4 BANDS PARAMETRIC EQUALIZER 30 ~ 70Hz, 150 ~ 400Hz, 1.5K~ 4KHz, 10K ~ 25KHz,**
- **4 BANDS EQUALIZER BOOST/ CUT 18dB, GAIN UP TO 8VOLTS RMS OUTPUT**
- **SUBWOOFER OUTPUT-LEVEL/ FREQUENCY 32 ~ 420Hz ADJ. CONTROL**
- **BUILD-IN ELEC. CROSSOVER FRONT/ REAR 32 ~ 420Hz ADJ. (-18dB/ Octave)**
- **INPUT SELECT FOR MAIN/ AUX, INDIVIDUAL SENSITIVITY CONTROL**
- **PRE-AMP VOLUME CONTROL FOR 4 CHANNEL OUTPUT SYSTEMS**
- **PRE-AMP FADER ADJUSTABLE FOR FRONT/ REAR OUTPUT SYSTEMS**
- **GOLD-PLATED RCA INPUT CONNECTORS, ALL VR'S PUSH-LOCK MECHANISM**
- **ON-BOARD 30V BI-POLAR SWITCHING POWER SUPPLIER, NIGHT ILLUMINATION**

SPECIFICATIONS:

5 band Parametric: 30 ~ 70Hz, 150 ~ 400Hz, 1.5K~ 4KHz, 10K ~ 25KHz, **Boost/ Cut:** 18dB.
Sub. Freq.: 35 ~ 250Hz. **Crossover:** 32 ~ 420Hz, **Bandwidth:** spec. to each band-Hi Shelving.
Frequency Response: 10Hz ~ 50KHz, +/- 1dB, **Input/ Output Impedance:** 10 K Ω / 50K Ω ,
S/N ratio: 105dB/ Ref. 1V Input. **Stereo Separation:** 75dB/ 1KHz.
Input Sensitivity: 50mV ~ 3Volts RMS, **Max. Output:** 8V RMS. **THD:** 0.005%.
Operating Voltage: 11 ~ 15V Negative ground. **Size(HxWxD):** 24m/m x 178m/m x 112m/m

<http://www.easoco.com.tw>