

EASO STEREO CO., LTD.

E-mail: audiopro@ms10.hinet.net
easoco@ms17.hinet.net

4F, No.951, Chung-Cheng Rd., Chung-Ho City.

Taipei. 235 Taiwan. R.O.C.

Tel: 886-2-8228 1100 Fax: 886-2-8228 6101

4 BAND GRAPHIC EQUALIZER PRE-AMP WITH SUBWOOFER OUTPUT



MODEL NO.: EMQ-P025

OEM and ODM orders are welcome

- **4 BANDS GRAPHIC EQUALIZER WITH 12dB BOOST/ CUT**
- **SUBWOOFER FREQUENCY SELECTORS/OUTPUT-LEVEL CONTROL**
- **INPUT SELECTOR SWITCH THE RADIO INPUT OR CD INPUT**
- **PRE-AMP FADER OUTPUT FOR 4 CHANNEL SYSTEMS**
- **GOLD-PLATED RCA INPUT CONNECTORS**
- **OPTION TWO COLOR NIGHT LIGHT OR TRANSPARENT TOP COVER**

SPECIFICATIONS:

4-band Parametric: Bass 150Hz, Mid.-Bass 400Hz, Mid 2.5KHz, Hi 15KHz. Boost/Cut: 12dB. Subwoofer frequency: 43/60Hz Bandwidth: specific to each band-Hi Shelving. S/N ratio: 95dB/ REF 1V Input. THD: 0.05% Input sensitivity: 150mV. Input/Output Impedance: 20 K Ω /50K Ω Stereo Separation: 75dB/1KHz. Operating Voltage: 11-15V Negative ground. Size(H \times W \times D) :34m/m x 178m/m x 112m/m

<http://www.easoco.com.tw>